

## Lighting Your Life Since 1970

Product Specifications - 85133ICSN		
Job Name:	Job Type:	
Quantity:	Comments	



## 85133ICSN **Basix EE 3-Light Bath Vanity**





**Finish** Satin Nickel

I am	nina
Laiii	pilig
A1	

Number of Bulbs	3
Light Type	Fluorescent
Bulb Type	GU24
Max Bulb Wattage	13
Max Fixture Wattage	39
Rated Life	±10,000 Hours
Rated Lumens	±2,700
Color Temp	±2,700 K
Bulb(s)	Included
Light Up/Down	Both
Beam Spread	N/A
CRI	81-82
Photo Cell Included	N/A
Ballast/Driver/Transformer	No
Dimmable	No

GI	lass/	'Sh	ac	le
1				

Ice

Measurements	
measurement	•

Width	19.00"
Height	8.00"
Length	N/A
Extension	9"
Back Plate Width	5.38"
Back Plate Height	5.38"
НСО	2.62"
Min Overall Height	0.00"
Max Overall Height	N/A
Hanging Weight	5.29 lbs
Height Adjustable	N/A
Slope	N/A
Chain Length	N/A
Wire Length	N/A
Canopy Width	N/A
Canopy Height	N/A
Canopy Length	N/A

# **Product Category**

**Bath Vanity** 

### Shipping

Jilippilig	
Carton Weight	6.55 lbs
Carton Width	9'
Carton Height	11'
Carton Length	17'
Carton Cubic Feet	0.99
Master Pack	1
Master Pack Weight	N/A
Master Pack Width	N/A
Master Pack Height	N/A
Master Pack Length	N/A
Master Cubic Feet	N/A
UPS Shippable	Yes

Cortification

Certification	
Safety Rating	Damp
Energy Star	Yes
CA Title 24	Yes
CA Title 20	No
ADA	No
Dark Sky	N/A

- 1	n	п	n	Δ	r
		ш	ш	C	

Other	
UPC Code	783209058668
Shades Included	N/A
Crystals Included	N/A
Diffuser Included	N/A
Conversion Kit	N/A
Material	Iror

#### **Equivalents**

Incandescent Watts	245
Fluorescent Watts	N/A

Maxim Lighting International and all designs, logos and images © 2015 Maxim Lighting International. All Rights Reserved. Maxim Lighting International reserves the right, at any time, to make changes in the design and/or construction of the product including the discontinuation of product without prior notice. Color may vary from what is pictured above due to limitations inherent to photographic processes.

Always consult a qualified, licensed electrician before installation of any product weighing 35 pounds or more. We recommend that a qualified, licensed electrician do the installation. Always install to a mechanically sound structure.