

Lighting Your Life Since 1970

	Product Specifications - 85134ICSN			
ĺ	Job Name:	Job Type:		
ĺ	Quantity:	Comments		



85134ICSN **Basix EE 4-Light Bath Vanity**



Finis	sh
Satin	Nickel

Lamping

Number of Bulbs 4 **Light Type** Fluorescent GU24 **Bulb Type** Max Bulb Wattage 13 Max Fixture Wattage 52 **Rated Life** ±10,000 Hours **Rated Lumens** ±3,600 **Color Temp** ±2,700 K Bulb(s) Included Light Up/Down Both **Beam Spread** N/A 81-82 **Photo Cell Included** N/A Ballast/Driver/Transformer No Dimmable No

Glass/Shade	
Ice	

Measurements	
Width	27.50"
Height	8.00"
Length	N/A
Extension	9"
Back Plate Width	5.38"
Back Plate Height	5.38"
НСО	2.62"
Min Overall Height	0.00"
Max Overall Height	N/A
Hanging Weight	6.17 lbs
Height Adjustable	N/A
Slope	N/A
Chain Length	N/A
Wire Length	N/A
Canopy Width	N/A
Canopy Height	N/A
Canopy Length	N/A

Product Category

Bath Vanity

9	hi	in	ni	in	α	
0	,,,	μ	P!		9	
_						

Jilippilig	
Carton Weight	9.50 lbs
Carton Width	11"
Carton Height	10"
Carton Length	27"
Carton Cubic Feet	1.71
Master Pack	1
Master Pack Weight	N/A
Master Pack Width	N/A
Master Pack Height	N/A
Master Pack Length	N/A
Master Cubic Feet	N/A
UPS Shippable	Yes

Certification

o o i i i i o a i o i i	
Safety Rating	Damp
Energy Star	Yes
CA Title 24	Yes
CA Title 20	No
ADA	No
Dark Sky	N/A

Other	
IPC Code 78320905988	
Shades Included	N/A
Crystals Included	N/A
Diffuser Included	N/A
Conversion Kit	N/A
Material	Iron

Equivalents

Incandescent Watts	327
Fluorescent Watts	N/A

Maxim Lighting International and all designs, logos and images © 2015 Maxim Lighting International. All Rights Reserved. Maxim Lighting International reserves the right, at any time, to make changes in the design and/or construction of the product including the discontinuation of product without prior notice. Color may vary from what is pictured above due to limitations inherent to photographic processes.

Always consult a qualified, licensed electrician before installation of any product weighing 35 pounds or more. We recommend that a qualified, licensed electrician do the installation. Always install to a mechanically sound structure.